

ALT Series - AC High Voltage

The ALT-130/60 and ALT-130/60F from our ALT Series of field portable AC hipot test sets are primarily designed for testing the dielectric strength of aerial lifts, booms, bucket trucks and liners per the ANSI 92.2 standard. With a continuously adjustable AC voltage, 2 range voltmeter, multi range current meter and built in timer, the ALT Series are also a great choice for a pass/fail, AC over-voltage withstand testing on larger capacitive loads such as switchgear, buss duct or other substation apparatus. A gapped core transformer for up to 7.2 kVA of output power with the draw of 3.6 kVA so the hipot can be powered by a 30A, 120Vac or 15A, 230Vac input. For lower power requirements please see our **PFT Series** and **ABT Series**. For higher power

- multipliers

- Guard/Ground circuit for accurate leakage current measurement
- Gapped core transformer design for capacitive load compensation
- Zero Start and External safety Interlock provisions

Model	ALT-130/60 / ALT-130/60F
Input	(ALT-130/60) 120 V, 60 Hz, 30 A (ALT-130/60F) 230 V, 50/60 Hz, 15 A
Output	0-130kV AC / 0-60 kV AC, 3.6 kVA resistive load Up to 7.2KVA capacitive load (1.3 nF @ 130kV or 5.3nF @ 60kV, 60 Hz) Output current is reduced at lower voltages
Duty	7.2 kVA: 1 hour ON, 2 hour OFF 4 kVA: continuous
Voltmeter	3.5", scaled 0-30/60kV & 0-60/130kV kV AC, ±2% F.S.
Current Meter	3.5", scaled 0-250uA and 0-1.0mA $\pm 2\%$ F.S. with range multipliers of x1, x10, x100
Distortion	Less than 5%
Size & Weight (W x D x H)	Control: 21 x 11.5 x 15.5 in., 46 lb. 533 x 292 x 394 mm, 21 kg HV Tank: 15.5 x 15.5 x 27.5 in., 160 lb. (225 lb. w/ Handtruck) 394 x 394 x 699 mm, 73 kg (102.5 kg w/ Handtruck)
Output Termination	Top toroid (0-130 kV) 1 inch ball side tap (0-60 kV)
Scope of Supply	20ft black ground lead, 20ft shielded return cable, external interlock plug, handtruck, operations manual, calibration certificate

requirements see our FPA, HPA and PAR lines. Secondary connected 2 Range Voltmeter: 0-30/60kV & 0-60/130kV 2 Range Current Meter: 0-250uA and 0-1.0mA with x1, x10, x100 • Full 7.2 kVA, 60kV tap for bucket liner testing • Fixed overload set to 120% of variable transformer rated output current • Transit protected meters prevent meter damage between test sites



ALT-130/60

ALT-130/60F 0 - 60 / 130 kV AC, up to 7.2 kVA

Optional Accessories

Hand & Foot Safety Switches





Safety Ground Sticks





Optional Upgrades

Digital Metering – Add Suffix "D" Secondary Cap Cancel Circuit - PN 90-225













